

F1201.2

F1201.2 offers the potential for use as a full range cabinet, providing balanced low frequency down to 80Hz.

Equally at home as part of a small front of house system or as fills in larger systems, F1201.2 is a versatile tool for both installers and rental users.

An integrated flared bass reflex port minimises turbulence and maximises our refined cabinet tuning. A high resolution 1" HF device and Funktion-One designed waveguide delivers precise high frequencies to 20kHz. F1201.2 benefits from our minimalist approach to passive crossover design, achieving very low distortion and excellent integration between drivers, to give a stable and engaging image. NL4 and Phoenix connector variants are combined into a common connector panel, simplifying purchasing and inventory management.

Combine with BR118 for a powerful, compact mobile system.



- Features:
- Compact enclosure with high output
  - High sensitivity/electroacoustic energy efficiency
  - Minimalist passive crossover design for maximum resolution
  - Dual NL4 and Phoenix connector combination as standard
  - Various mounting/rigging options (yoke, wall bracket)
  - M8 rigging points
  - Integrated 35mm pole mount
  - Weather resistant IP55 version available
- Frequency Response (-3dB): 55Hz - 20kHz
- Weight: 21kg (46.3lbs)
- Nominal Dispersion: 90° Horizontal x 60° Vertical
- Connectors: 2 x Neutrik NL4 and Phoenix

Driver	Crossover Frequencies	Sensitivity (At 1m)	Power (AES)	Nominal Impedance
12" + 1"	85Hz - Up	100dB at 2.8V	350W	8Ω

\*Measured in free field

Specific crossover settings can be found at [www.funktion-one.com/support](http://www.funktion-one.com/support)

